

HDMI to CV/SV Converter

CV-HCS103A

QUICK INSTALLATION GUIDE

© Digitogo, Inc. (D2G) www.digitogo.com

PACKAGE CONTENTS

- HDMI to CV/SV Converter unit x 1
- Locking DC 5V 2A Power Adapter x 1
- AC Power Cord x 1
- Quick Installation Guide x 1

PANEL DESCRIPTION



| HDMI Input Indicator | Power Indicator |
|----------------------|------------------------|
| 3 DIP Switch | DIP Setting Confirm |
| 5 Power Input | 6 HDMI Input |
| 7 HDMI Output | 8 HDMI Output |
| Audio Output | Component Video Output |
| S-Video Output | |

INSTALLATION

- 1. Power off all connecting equipment prior to installation such as video player, display monitor.
- 2. Connect HDMI cable from "HDMI Input" to video source.
- 3. Connect converter to displays and audio speakers. There are three sets of outputs available. All outputs work simultaneously.
 - HDMI Output and Audio Out: provides the same resolution as "HDMI Input"
 - Component Video Output- video is scaled down to PAL or NTSC format depending on user setting (default setting is NTSC)
 - S-Video Output- video is scaled down to PAL or NTSC format depending on user setting (default setting is NTSC)
- 4. Connect Converter to power source and turn on the power.
- 5. "HDMI Input Indicator" lids when input is successfully connected to converter. However, when input is from a DVI source through a connector, the Indicator is disabled.
- 6. Switch on all connecting devices, ie, display source, audio source (optional) and monitor.
- 7. Use "DIP Switch" and "SET" button to select desired format and scan mode.

| NO | Α | Mode | |
|----|---|------|--|
| 1 | 0 | PAL | |
| 2 | 1 | NTSC | |

| ИО | В | С | Mode |
|----|---|---|------------|
| 3 | 0 | 0 | Under Scan |
| 4 | 0 | 1 | Over Scan |
| 5 | 1 | 0 | Pan Scan |

DIAGRAM

