

DVI Switch with Audio

Model Number: SW-DE201A, SW-DE401A

OVERVIEW

Digitogo's DVI Switch with Audio can select between multiple DVI and stereo audio sources by using IR Remote or panel buttons, and output to one DVI display and stereo audio device.

Built-in EDID functionality allows the user to choose between the Default EDID on the switch or copies EDID from your DVI Output Display. In the case of an unexpected disconnection or power shortage, the switch will automatically restore the last EDID configuration. This ensures uninterrupted EDID communication and maintains crystal clear image at all times.

FEATURES

- Seamless switching between multiple DVI devices to one screen
- Support HD 1080p and 1920x1200 resolution
- Higher video bandwidth to ensure optimal sharpness and brightness
- Easy selection via panel button or remote control
- Automatic EDID detection include built-in cache

SPECIFICATIONS

Model No.	SW-DE201A	SW-DE401A
Input	DVI x 2	DVI x 4
	3.5mm Phone Jack x 2 (stereo)	3.5mm Phone Jack x 4 (stereo)
Output	DVI x 1	
	3.5mm Phone Jack x 1 (stereo)	
Resolution	Up to VGA 1920 x 1200 resolution @ 60Hz	
Supported Audio Format	Stereo Audio	
Power Supply	DC5V 1A	
Max Power Consumption	150mA	
Video Bandwidth	225MHz	
Casing	Metal	
Dimensions (mm)	210 x 73 x 39	
Net Weight	540g	560g
Operating Temperature	0° C ~48° C	
Storage Temperature	-20° C ~ 60° C	
Relative Humidity	0~80% RH	

PACKAGE CONTENTS

- DVI Switch unit x 1
- Locking DC5V 1A Power Adapter x 1
- AC Power Cord x 1
- Quick Installation Guide x 1
- Remote Control x 1